

CHANGSHA TAIHE ELECTRONIC EQUIPMENT CO.,LTD.

Pressure Sensor | Temperature Sensor | Liquid Level Sensor | Load Cell | Smart Instruments




Position sensor | Torque | Internet of Things



16

Years of experience in sensor R&D,
manufacturing and production

Provide one-stop customization services
for various sensors

Product Image	Model & Name	Dimensional Drawing	Partial Technical Specifications
	PPM-WZP Temperature sensor		Temperature Measuring Element: Pt100,Pt1000 Use Temperature: -200~600°C,customized Thread: M6,customized Accuracy: $\pm 0.5^{\circ}\text{C}$,customized Probe Diameter: 3mm,customized Probe Length: 30mm,customized Cable Material: Teflon Material: Stainless steel
	PPM-WZP-2088 Temperature transmitter		Temperature Measurement Range: -200~1600°C Power Supply: 12~32VDC Output Signal: 4~20mA,0~5VDC,0~10VDC Accuracy: 0.1%FS,0.2%FS,0.5%FS Thermal Impact Time: 0.3S,1S,10S Operating Abient Temperature: -40~85°C Ambient Temperature Effect: 0.25%FS/10°C Protection Level : IP65 Protective Tube Material: Stainless steel,nickel alloy Protective Tube Diameter: $\Phi 4\sim 6,\Phi 18,$ $\Phi 20,\Phi 22,\Phi 28,\Phi 35,\Phi 40$ or customized Insertion Length: 50,100,150,200,300, 400,500,750,1000 or customized Nominal Pressure: $\leq 20\text{MPa},\leq 10\text{MPa},$ $\leq 4\text{MPa},\leq 2.5\text{MPa}$ optional at atmospheric pressure
	PPM-WZPB Temperature transmitter		Temperature Measurement Range: -200~600°C Power Supply: 9~36VDC Output Signal: 4~20mA,RS485 Accuracy: 0.5%FS,customized Nominal Pressure: $\leq 4\text{MPa}$,customized Operating Abient Temperature: -40~85°C Ambient Temperature Effect: 0.25%FS/10°C Protective Tube Diameter: $\Phi 4,\Phi 6,\Phi 8$ or customized Insertion Length: 20,50,100 or customized Nominal Pressure: $\leq 4\text{MPa}$ or customized Temperature Measuring Element: Pt100,Pt1000,customized

CONTACT US

www.csppmSensor.com

Address: No. 188, Huanbao Road, Yuhua Zone, Changsha, Hunan, China

E-mail: info@csppm.com

Mobile | Wechat | WhatsApp: +86 19118913383